

CDP-S 系列

CDP-S

技术参数

规格型号	CDP1K(L)-S	CDP2K(L)-S	CDP3K(L)-S	CDP6K(L)-S	CDP10K(L)-S
额定容量	1000 VA / 800 W	2000 VA / 1600 W	3000 VA / 2400 W	6000 VA / 4800 W	10000 VA / 8000 W
输入	单进单出				
输出电压	180 VAC ± 3.0% / 210 VAC ± 3.0% / 230 VAC ± 3.0% (基于负载范围: 100% - 80% / 80% - 70% / 70 - 60% / 60% - 0)			110 VAC ± 3% / 230 VAC ± 3% / 240 VAC ± 3% / 250 VAC ± 3% (基于负载范围: 100% - 80% / 80% - 70% / 70 - 60% / 60% - 0)	
电压范围	100 VAC / 115 VAC / 120 VAC / 128 VAC ± 5% (基于负载范围: 100% - 80% / 80% - 70% / 70 - 60% / 60% - 0)			110 VAC ± 3% / 230 VAC ± 3% / 240 VAC ± 3% / 250 VAC ± 3% (基于负载范围: 100% - 80% / 80% - 70% / 70 - 60% / 60% - 0)	
高压转换	300 VAC ± 5%			300 VAC ± 3%	
效率	20% VDC @ 100% 负载			20% VDC @ 100% 负载	
效率	40% VDC @ 100% 负载			40% VDC @ 100% 负载	
效率	60% VDC @ 100% 负载			60% VDC @ 100% 负载	
效率	80% VDC @ 100% 负载			80% VDC @ 100% 负载	

50 Hz ± 0.2 Hz 或 60Hz ± 0.2 Hz			50 Hz ± 0.1 Hz 或 60 Hz ± 0.1 Hz		
3:1			3:1 (最大)		
≤ 3% THD (阻性负载), ≤ 6% THD (非线性负载)			≤ 3% THD (阻性负载), ≤ 5% THD (非线性负载)		
0ms			0ms		
4 ms (一般)			0ms		
纯正弦波			纯正弦波		
88%	88%	90%	92%	93%	
83%	85%	88%	90%	91%	

12 V / 7 Ah				12 V / 7 Ah				12 V / 7 Ah				12 V / 9 Ah				12 V / 9 Ah							
2		4		6		6		16		16		16		16		16							
4小时充至90%								9小时充至90%															
1.0 A								预设: 1.0 A ± 10% 最大: 2.0 A ± 10%															
27.4 VDC ± 1%		54.7 VDC ± 1%		82.1 VDC ± 1%		82.1 VDC ± 1%		218.4 VDC ± 1%															
取决于申请商																							
3		6				8				16节 (可增16 - 20节)				16节 (可增16 - 20节)									
1.0A/2.0A/4.0A/6.0 A								预设: 4.0 A ± 10%, 最大: 6.0 A ± 10%															

负载大小, 电池容量, 市电模式, 电池模式, 旁路模式, 故障指示	UPS状态, 负载大小, 电池容量, 输入输出电压, 卸载时间, 故障情况
------------------------------------	---------------------------------------

每1秒一声	连续鸣响
(mm) 145 x 282 x 100	145 x 282 x 100
145 x 282 x 100	145 x 282 x 100
145 x 282 x 100	145 x 282 x 100

4.1	7	7.5	12	16
70-90 % RH @ 0-40°C (不结露), 小于 50dB(A) @ 1 Meter			0-95% RH @ 0-40°C (不结露), 小于 55dB(A) @ 1 Meter	
支持Windows® 2000/2003/XP/Vista/2008, Windows® 7/8, Linux, Unix, and MAC				

标准机	数量
长机	标准充电时间
	最大充电电流
	充电电压
	电池型号
	容量
	最大充电电流
	电池电压
	显示说明
	LCD带LED显示
	警告声音